

Fenêtre	Onglet	Paramètre	Valeurs			Nom dans l'Application	OSC
			Min	Max	Défaut		
VideoMixer	Feedback	PolyMap_VideoMixer_Feedback_ScaleR	1.	1.1	1.	Rouge	/PolyMap/VideoMixer/Feedback/R
VideoMixer	Feedback	PolyMap_VideoMixer_Feedback_ScaleG	1.	1.1	1.	Vert	/PolyMap/VideoMixer/Feedback/V
VideoMixer	Feedback	PolyMap_VideoMixer_Feedback_ScaleB	1.	1.1	1.	Bleu	/PolyMap/VideoMixer/Feedback/B
VideoMixer	Feedback	PolyMap_VideoMixer_Feedback_ZoomY	-5.	5.	1.	Zoom vertical	/PolyMap/VideoMixer/Feedback/ZoomV
VideoMixer	Feedback	PolyMap_VideoMixer_Feedback_ZoomX	-5.	5.	1.	Zoom horizontal	/PolyMap/VideoMixer/Feedback/ZoomH
VideoMixer	Feedback	PolyMap_VideoMixer_Feedback_EraseColorAlpha	0.	1.	1.	Niveau	/PolyMap/VideoMixer/Feedback/Niveau
VideoMixer	Feedback	PolyMap_VideoMixer_Feedback_OffsetX	-100.	100.	0.	Gauche / Droite	/PolyMap/VideoMixer/Feedback/GD
VideoMixer	Feedback	PolyMap_VideoMixer_Feedback_OffsetY	-100.	100.	0.	Haut / Bas	/PolyMap/VideoMixer/Feedback/HB
VideoMixer	Feedback	PolyMap_VideoMixer_Feedback_Theta	-360	360.	0.	Rotation	/PolyMap/VideoMixer/Feedback/Rotation
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_ServerName	0	[n°_de_source]	0	Source	/PolyMap/VideoMixer/Layer[1-10]/Source
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_ServerName	[nom_source]	NONE	NONE	Source	/PolyMap/VideoMixer/Layer[1-10]/Source/name
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_Zoom	-2.	2.	1.	Taille	/PolyMap/VideoMixer/Layer[1-10]/Zoom
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_OffsetX	-1.5	1.5	0.	Gauche / Droite	/PolyMap/VideoMixer/Layer[1-10]/Offset/X
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_OffsetY	-1.	1.	0.	Haut / Bas	/PolyMap/VideoMixer/Layer[1-10]/Offset/Y
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_Theta	-360.	360.	0.	Rotation	/PolyMap/VideoMixer/Layer[1-10]/Rotation
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_Color	0.	1.	1.	Niveau	/PolyMap/VideoMixer/Layer[1-10]/Niveau
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_ActivateFeedback	0	1	0	Feedback	/PolyMap/VideoMixer/Layer[1-10]/Feedback/Activate
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_ActivateScaleBias	0	1	0	ScaleBias	/PolyMap/VideoMixer/Layer[1-10]/ScaleBias/Activate
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_Scale	-10.	10.	1.	Scale	/PolyMap/VideoMixer/Layer[1-10]/ScaleBias/Scale
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_Bias	-10.	10.	0.	Bias	/PolyMap/VideoMixer/Layer[1-10]/ScaleBias/Bias
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_ActivateSobel	0	1	0	Sobel	/PolyMap/VideoMixer/Layer[1-10]/Sobel/Activate
VideoMixer	Layer[1-10]	PolyMap_VideoMixer_Layer1-10_Sobel	0.	1.	0.	Sobel	/PolyMap/VideoMixer/Layer[1-10]/Sobel/Sobel
VideoMixer	Memoires	PolyMap_VideoMixer_Presets_Menu_index	0	[nb_de_memoire]	0	(menu mémoire)	/PolyMap/VideoMixer/Preset
VideoMixer	Memoires	PolyMap_VideoMixer_Presets_Menu	[nom_memoire]	NONE	NONE	(menu mémoire)	/PolyMap/VideoMixer/Preset/name
Mappings	Memoires	PolyMap_Mappings_Presets_Menu_index	0	[nb_de_memoire]	0	(menu mémoire)	/PolyMap/Mappings/Preset
Mappings	Memoires	PolyMap_Mappings_Presets_Menu	[nom_memoire]	NONE	NONE	(menu mémoire)	/PolyMap/Mappings/Preset/name
Main	Memoires	PolyMap_Presets_Menu_index	0	[nb_de_memoire]	0	(menu mémoire)	/PolyMap/Main/Preset
Main	Memoires	PolyMap_Presets_Menu	[nom_memoire]	NONE	NONE	(menu mémoire)	/PolyMap/Main/Preset/name